

Motorola Ming A1200 Data setup



OLD

Internet mms setup

Go to menu(top left button)< Go to set up< data network<

Profile Name: Chinook MMS
GPRS Setting APN: wap.chinookwireless.com
Primary Gateway:63.99.231.135
Port: 8080
Save & Connect

Go to Menu< Go to browser< Go to set up< Profiles

Edit internet
Profile name: web.chinookwireless.com
Change network link to Chinook MMS
Save

Go to messages 3rd button on top< go to service set up< go to multimedia message
Default profile: Chinook MMS
Edit Chinook MMS
Profile name: Chinook MMS
MMSC: mms.chinookwireless.com/servlets/mms
Network profile: Chinook MMS
Edit Chinook MMS to connect via Chinook MMS
Save
Set as default
Save

Power Cycle Phone

NEW

NETWORK CONNECTION

Select > Top left Icon with the 4 Dots

Tap Setup

Tap Data Network

Tap Bottom Left Icon

Select > New

Profile Name: ChinookMMS

GPRS Setting: APN: **wapgw.chinookwireless.net**

User Name: Blank

Password: Blank

Timeout: Off

Primary Gateway IP: **204.181.155.195**

Port: **8080**

Secondary Gateway IP: Blank

Port: 0

DNS Server: Blank

CSD Setting: Blank

Dial in number: Blank

Query at Logon: Blank

User Name: Blank

Password: Blank

Baud Rate: Auto

Line Type: Modem

Timeout: Off

DNS Server: Blank

MMS SETUP

Select Envelope Icon at the top of the screen > Select Bottom Left Icon > Select Service Setup > Select Multimedia Message >

Profile Name: chinookMMS

Bottom left icon again

MMSC: **http://mms.cellonation.net/mms/**

Max Sending Size: 300k

Network Profile: ChinookMMS

Internet setup:

Go to Menu< Go to browser< Go to set up< Profiles

Edit internet

Profile name: **Cellular_One**

Change network link to Chinook MMS

Save