

HTC S621 Internet/MMS set-up



Internet/MMS Set Up

Press the left softkey to access the start menu
Go into the settings folder and access option 6 for '**Connections**'
Next, choose option 5 for '**GPRS**'
Press the right softkey and choose '**Add**'

Description: **Internet**

Connects to: choose '**The Internet**'

Access point name will read "internet.chinookwireless.com"

CHANGE Access point name to "**internet.chinookwireless.net**"

Username: Blank

Password: Blank

Primary DNS: Blank

Secondary DNS: Blank

IP address: Blank

Done

Repeat process for a second time

Description: **MMS**

Connects to: choose '**WAP Network**'

Access point name will read "wap.chinookwireless.com"

CHANGE Access point name to "**wapgw.chinookwireless.net**"

Username: Blank

Password: Blank

Primary DNS: Blank

Secondary DNS: Blank

IP address: Blank

Done

For MMS:

Press left softkey to access start menu

Go into '**messaging**'

Scroll down to '**MMS**'

With it highlighted (do not go into it), press the right softkey for '**Menu**'

Select '**Settings**'

While in settings, press right softkey for '**Menu**' again

Choose option 1 '**MMSC Settings**'

Highlight the default set-up and hit right softkey for '**Menu**'

Choose option 2 to '**Edit**'

Change the name to '**Chinook MMS**'

MMS URL will read "http://mms.chinookwireless.com/servlets/mms"

CHANGE MMSC URL to "**http://mms.cellonenation.net/mms/**"

WAP gateway will read "63.99.231.135"

CHANGE WAP gateway to "**204.181.155.195**"

Port: **8080**

Connect via: **WAP Network**

Max. Sending size: Default

WAP version: **WAP 2.0**

DONE